7. Electrical Parts List

7-1 CS1448X/NWT(CS1448X/BWT and CS1448X/NWT Dissimilar Parts)

Loc. No.	Code No.	Description ; Specification	Remark

ASSY PCB MAIN(OPT)

*	AA94-02069J	ASSY PCB MAIN(OPT);CS1448X/NWT,KS1A,UKRAINE,-

ASSY ACCESSORY

	AA68-01010A	MANUAL USERS;-,-,B5,-,W/P100(G),-,-,1,-,- ,KS1A,TTX,32P,UKRAINE

7-2 CS1448X/VWT(CS1448X/BWT and CS1448X/VWT Dissimilar Parts)

Loc. No.	Code No.	Description ; Specification	Remark

ASSY PCB MAIN(OPT)

*	AA94-02066X	ASSY PCB MAIN(OPT);CS1448X/VWT,KS1A,RUSSIA,-

7-3 CS2039X/BWT(CS1448X/BWT and CS2039X/BWT Dissimilar Parts)

Loc. No.	Code No.	Description ; Specification	Remark

ASSY PCB MAIN(OPT)

*	AA94-02066L	ASSY PCB MAIN(OPT);CS2039X/BWT,KS1A,RUSSIA,-
CN603	3711-002643	CONNECTOR-HEADER;BOX,4P,1R,2.5mm,STRAIGHT,SN
CR410S	2306-000327	C-FILM,MPPF;6.3nF,3%,1.6KV,TP,28.5x18x10,2
LC801S	AA27-20003X	COIL-DEGAUSSING;-,20,14.4ohm,48T,L2170,E
R405	2001-001187	R-CARBON(S);75OHM,5%,1/2W,AA,TP,2.4X6.4MM
R501H	2002-001008	R-COMPOSITION;1.8Kohm,10%,1/2W,AA,TP,3.7x9mm
R502H	2002-001008	R-COMPOSITION;1.8Kohm,10%,1/2W,AA,TP,3.7x9mm
R601	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM
R814	2008-001116	R-FUSIBLE(S);0.68ohm,10%,2W,AG,TP,3.9x12mm
R815	2008-001116	R-FUSIBLE(S);0.68ohm,10%,2W,AG,TP,3.9x12mm
⚠ V999S	3704-001105	SOCKET-CRT;11P,20PI,26.5PI,NI,-

ASSY CABINET FRONT

*	AA91-00120P	ASSY CABINET FRONT;-,5039 CIS,(SPK)B708P PROGUN II,HB,BLK
CB+RCA	6002-000514	SCREW-TAPPING;RH,+,2,M4,L15,ZPC(BLK),SWRCH18
CRT+CF	AA60-10050R	SCREW-ASSY;WC,HH,+,M5,L31.5,SWRCH18A,ZPC(
KNPOMA	AA61-60003J	SPRING-CS;-,SUS304,0.5,OD6,H12,N7,-,-,-
SPK+CF	6003-001019	SCREW-TAPTITE;RH,+,B,M4,L12,ZPC(BLK),SWRCH18
	AA63-50011B	GRILLE-WOOFER;-,5039,PA110,SECC,T0.5,-,-
	AA64-00261N	CABINET FRONT;5039,BK708P CIS PROGUN II,HIPS,HB,BLK
	AA61-40015A	BOSS-CABINET;-,HIPS,HB,NTR,-,-
	AA64-10048A	KNOB-CONTROL;-,5039,-,ABS,HB,BLK
	AA64-10144A	KNOB-POWER,M;-,5039,-,ABS,HB,BLK
	AA64-40055A	WINDOW-REMOCON;-,5039,-,PC,VO,VIOLET,-
	AA64-40167A	INDICATOR-LED;-,5039,-,ACRYL,-,-,-
	AA64-70123B	BADGE-BRAND;AL,R2000,SILVER,L=50,SAMSUNG,-
	AA96-10137B	ASSY-SPEAKER;-,8OHM,3W,3001-001020,AA39-20505M,R700/L350
	3001-001020	SPEAKER;3W,8ohm,90dB,140Hz

Loc. No.	Code No.	Description ; Specification	Remark
	AA39-20505M	LEAD CONNECTOR-ASSY;-,YSH025-04,REC,4P,350,700mm,	
	AA64-30389D	CABINET-BACK;-,5039,-,HIPS,V2,BLK,-,-	
	AA65-30107A	CLAMP-D,COIL;NYLON 66,V2,NTR,-,20~22 INCH,-	

ASSY-CRT

⚠	AA03-10029W	CRT-COLOR;-,A48KRD82X(H),+380mG,20,90de	
	AA27-00002A	MAGNET-CONVERGENCE;-,JH291-SC-OB,29.1MM	
⚠	AA27-50004W	DEFLECTION-YOKE;-,DSE-1992LL(1H),20'/A48KRD82X	

ASSY ACCESSORY

	AA63-00261B	COVER-JACK;-,2139,BK708P,HIPS,HB,G4309,-,-	

REMOCON

*	AA59-00104D	REMOCON;-,TM59,SIM806E,24,L/GRAY,-,PAL-MONO,-,-,-,-	

7-4 CS2039X/NWT(CS1448X/BWT and CS2039X/NWT Dissimilar Parts)

Loc. No.	Code No.	Description ; Specification	Remark

ASSY PCB MAIN(OPT)

*	AA94-02069R	ASSY PCB MAIN(OPT);CS2039X/NWT,KS1A,UKRAINE,-	
CN603	3711-002643	CONNECTOR-HEADER;BOX,4P,1R,2.5mm,STRAIGHT,SN	
CR410S	2306-000327	C-FILM,MPPF;6.3nF,3%,1.6KV,TP,28.5x18x10,2	
LC801S	AA27-20003X	COIL-DEGAUSSING;-,20,14.4ohm,48T,L2170,E	
R405	2001-001187	R-CARBON(S);75OHM,5%,1/2W,AA,TP,2.4X6.4MM	
R501H	2002-001008	R-COMPOSITION;1.8Kohm,10%,1/2W,AA,TP,3.7x9mm	
R502H	2002-001008	R-COMPOSITION;1.8Kohm,10%,1/2W,AA,TP,3.7x9mm	
R601	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R814	2008-001116	R-FUSIBLE(S);0.68ohm,10%,2W,AG,TP,3.9x12mm	
R815	2008-001116	R-FUSIBLE(S);0.68ohm,10%,2W,AG,TP,3.9x12mm	
⚠ V999S	3704-001105	SOCKET-CRT;11P,20PI,26.5PI,NI,-	

ASSY CABINET FRONT

*	AA91-00120P	ASSY CABINET FRONT;-,5039 CIS,(SPK)B708P PROGUN II,HB,BLK	
CB+RCA	6002-000514	SCREW-TAPPING;RH,+,2,M4,L15,ZPC(BLK),SWRCH18	
CRT+CF	AA60-10050R	SCREW-ASSY;WC,HH,+,M5,L31.5,SWRCH18A,ZPC(	
KNPOMA	AA61-60003J	SPRING-CS;-,SUS304,0.5,OD6,H12,N7,-,-,-	
SPK+CF	6003-001019	SCREW-TAPTITE;RH,+,B,M4,L12,ZPC(BLK),SWRCH18	
	AA63-50011B	GRILLE-WOOFER;-,5039,PA110,SECC,T0.5,-,-	
	AA64-00261N	CABINET FRONT;5039,BK708P CIS PROGUN II,HIPS,HB,BLK	
	AA61-40015A	BOSS-CABINET;-,HIPS,HB,NTR,-,-	
	AA64-10048A	KNOB-CONTROL;-,5039,-,ABS,HB,BLK	
	AA64-10144A	KNOB-POWER,M;-,5039,-,ABS,HB,BLK	
	AA64-40055A	WINDOW-REMOCON;-,5039,-,PC,VO,VIOLET,-	
	AA64-40167A	INDICATOR-LED;-,5039,-,ACRYL,-,-,-	
	AA64-70123B	BADGE-BRAND;AL,R2000,SILVER,L=50,SAMSUNG,-	
	AA96-10137B	ASSY-SPEAKER;-,8OHM,3W,3001-001020,AA39-20505M,R700/L350	
	3001-001020	SPEAKER;3W,8ohm,90dB,140Hz	
	AA39-20505M	LEAD CONNECTOR-ASSY;-,YSH025-04,REC,4P,350,700mm,1	
	AA64-30389D	CABINET-BACK;-,5039,-,HIPS,V2,BLK,-,-	
	AA65-30107A	CLAMP-D,COIL;NYLON 66,V2,NTR,-,20~22 INCH,-	

ASSY-CRT

⚠	AA03-10029W	CRT-COLOR;-,A48KRD82X(H),+380mG,20,90de	
	AA27-00002A	MAGNET-CONVERGENCE;-,JH291-SC-OB,29.1MM	
⚠	AA27-50004W	DEFLECTION-YOKE;-,DSE-1992LL(1H),20'/A48KRD82X	

ASSY ACCESSORY

	AA63-00261B	COVER-JACK;-,2139,BK708P,HIPS,HB,G4309,-,-	
	AA68-01010A	MANUAL USERS;-,-,B5,-,W/P100(G),-,-,1,-,-,KS1A,TTX,32P,UKRAINE	

REMOCON

*	AA59-00104D	REMOCON;-,TM59,SIM806E,24,L/GRAY,-,PAL-MONO,-,-,-,-	

7-5 CS2039X/VWT(CS1448X/BWT and CS2039X/VWT Dissimilar Parts)

Loc. No.	Code No.	Description ; Specification	Remark

ASSY PCB MAIN(OPT)

*	AA94-02070S	ASSY PCB MAIN(OPT);CS2039X/VWT,KS1A,LITHUANIA,-	
CN603	3711-002643	CONNECTOR-HEADER;BOX,4P,1R,2.5mm,STRAIGHT,SN	
CR410S	2306-000327	C-FILM,MPPF;6.3nF,3%,1.6KV,TP,28.5x18x10,2	
LC801S	AA27-20003X	COIL-DEGAUSSING;-,20,14.4ohm,48T,L2170,E	
R405	2001-001187	R-CARBON(S);75OHM,5%,1/2W,AA,TP,2.4X6.4MM	
R501H	2002-001008	R-COMPOSITION;1.8Kohm,10%,1/2W,AA,TP,3.7x9mm	
R502H	2002-001008	R-COMPOSITION;1.8Kohm,10%,1/2W,AA,TP,3.7x9mm	
R601	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R814	2008-001116	R-FUSIBLE(S);0.68ohm,10%,2W,AG,TP,3.9x12mm	
R815	2008-001116	R-FUSIBLE(S);0.68ohm,10%,2W,AG,TP,3.9x12mm	
V999S	3704-001105	SOCKET-CRT;11P,20PI,26.5PI,NI,-	

ASSY CABINET FRONT

*	AA91-00120P	ASSY CABINET FRONT;-,5039 CIS,(SPK)B708P PROGUN II,HB,BLK	
CB+RCA	6002-000514	SCREW-TAPPING;RH,+,2,M4,L15,ZPC(BLK),SWRCH18	
CRT+CF	AA60-10050R	SCREW-ASSY;WC,HH,+,M5,L31.5,SWRCH18A,ZPC(	
KNPOMA	AA61-60003J	SPRING-CS;-,SUS304,0.5,OD6,H12,N7,-,-,-	
SPK+CF	6003-001019	SCREW-TAPTITE;RH,+,B,M4,L12,ZPC(BLK),SWRCH18	
	AA63-50011B	GRILLE-WOOFER;-,5039,PA110,SECC,T0.5,-,-	
	AA64-00261N	CABINET FRONT;5039,BK708P CIS PROGUN II,HIPS,HB,BLK	
	AA61-40015A	BOSS-CABINET;-,HIPS,HB,NTR,-,-	
	AA64-10048A	KNOB-CONTROL;-,5039,-,ABS,HB,BLK	
	AA64-10144A	KNOB-POWER,M;-,5039,-,ABS,HB,BLK	
	AA64-40055A	WINDOW-REMOCON;-,5039,-,PC,VO,VIOLET,-	
	AA64-40167A	INDICATOR-LED;-,5039,-,ACRYL,-,-,-	
	AA64-70123B	BADGE-BRAND;AL,R2000,SILVER,L=50,SAMSUNG,-	
	AA96-10137B	ASSY-SPEAKER;-,8OHM,3W,3001-001020,AA39-20505M,R700/L350	
	3001-001020	SPEAKER;3W,8ohm,90dB,140Hz	
	AA39-20505M	LEAD CONNECTOR-ASSY;-,YSH025-04,REC,4P,350,700mm,1	
	AA64-30389D	CABINET-BACK;-,5039,-,HIPS,V2,BLK,-,-	
	AA65-30107A	CLAMP-D,COIL;NYLON 66,V2,NTR,-,20~22 INCH,-	

ASSY-CRT

⚠	AA03-10029W	CRT-COLOR;-,A48KRD82X(H),+380mG,20,90de	
	AA27-00002A	MAGNET-CONVERGENCE;-,JH291-SC-OB,29.1MM	
⚠	AA27-50004W	DEFLECTION-YOKE;-,DSE-1992LL(1H),20'/A48KRD82X	

ASSY ACCESSORY

	AA63-00261B	COVER-JACK;-,2139,BK708P,HIPS,HB,G4309,-,-	

REMOCON

*	AA59-00104D	REMOCON;-,TM59,SIM806E,24,L/GRAY,-,PAL-MONO,-,-,-,-	

7-6 CS2139TX/VWT(CS1448X/BWT and CS2139TX/VWT Dissimilar Parts)

Loc. No.	Code No.	Description ; Specification	Remark

ASSY PCB MAIN(OPT)

*	AA94-02069F	ASSY PCB MAIN(OPT);CS2139TX/VWT,KS1A,LITHUANIA,-	
CN603	3711-002643	CONNECTOR-HEADER;BOX,4P,1R,2.5mm,STRAIGHT,SN	
CR402S	2306-000188	C-FILM,MPPF;330nF,5%,400V,TP,26x19.5x11,20	
CR410S	2306-000327	C-FILM,MPPF;6.3nF,3%,1.6KV,TP,28.5x18x10,2	
⚠ IC201S	AA09-00022A	IC-MCU;TDA9351/4-OTP,TDA9351/4,ST,-,64,SDIP,12KHz,8,6048,1uS,-,CMOS,-,8,PUS,-,MCU,750,3	
L403	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
LC801S	AA27-20004A	COIL-DEGAUSSING;-,21,14ohm,45T,L2380,E	
R302	2004-004366	R-METAL(S);1.3Kohm,1%,1/2W,AA,TP,2.5x6.5m	
R306	2004-001369	R-METAL(S);1.2Kohm,1%,1/2W,AA,TP,2.4x6.4m	
R315	2003-002009	R-METAL OXIDE(S);390ohm,5%,2W,AF,TP,3.9x10mm	
R316	2003-002009	R-METAL OXIDE(S);390ohm,5%,2W,AF,TP,3.9x10mm	
R405	2001-001116	R-CARBON(S);27OHM,5%,1/2W,AA,TP,2.4X6.4MM	
R501H	2002-001008	R-COMPOSITION;1.8Kohm,10%,1/2W,AA,TP,3.7x9mm	
R502H	2002-001008	R-COMPOSITION;1.8Kohm,10%,1/2W,AA,TP,3.7x9mm	
R601	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R814	2008-001116	R-FUSIBLE(S);0.68ohm,10%,2W,AG,TP,3.9x12mm	
R815	2008-001116	R-FUSIBLE(S);0.68ohm,10%,2W,AG,TP,3.9x12mm	
⚠ V999S	3704-001105	SOCKET-CRT;11P,20PI,26.5PI,NI,-	

ASSY CABINET FRONT

*	AA91-00086L	ASSY CABINET FRONT;-,2139,(SPK)BK708 PROGUN II,HB,BLK	
CABBAC	AA63-60001L	SPACER-FELT;FELT,T0.35,BLK,150X15,-,-	
CB+CF	6002-000514	SCREW-TAPPING;RH,+,2,M4,L15,ZPC(BLK),SWRCH18	
CB+RCA	6002-000514	SCREW-TAPPING;RH,+,2,M4,L15,ZPC(BLK),SWRCH18	
CRT+CF	AA60-10050R	SCREW-ASSY;WC,HH,+,M5,L31.5,SWRCH18A,ZPC(	
KNPOMA	AA61-60003J	SPRING-CS;-,SUS304,0.5,OD6,H12,N7,-,-,-	
PA+CF	AA60-10002A	SCREW-TAPPING;RH,+,M4,L12,ZPC(YEL),-,OD14	
SPK+CF	6003-001026	SCREW-TAPTITE;RH,+,B,M4,L15,ZPC(BLK),SWRCH18	
	AA63-50053B	GRILLE-WOOFER;-,5339,PA110,SECC,T0.5,-,-	
	AA64-00236L	CABINET FRONT;-,5339,BK708P CIS PROGUN II,HIPS,HB,BLK,-,-	
	AA61-40015A	BOSS-CABINET;-,HIPS,HB,NTR,-,-	
	AA64-10014A	KNOB-CONTROL;-,5339,-,ABS,HB,BLK	
	AA64-10185A	KNOB-POWER,M;-,5339,-,ABS,HB,BLK	
	AA64-40053A	WINDOW-REMOCON;-,5339,-,PC,V0,VIOLET,-	
	AA64-40186A	INDICATOR-LED;-,5339,-,ACRYL,-,-,-	
	AA64-70123B	BADGE-BRAND;AL,R2000,SILVER,L=50,SAMSUNG,-	
	AA96-10137B	ASSY-SPEAKER;-,8OHM,3W,3001-001020,AA39-20505M,R700/L350	
	3001-001020	SPEAKER;3W,8ohm,90dB,140Hz	
	AA39-20505M	LEAD CONNECTOR-ASSY;-,YSH025-04,REC,4P,350,700mm,1	

Loc. No.	Code No.	Description ; Specification	Remark
	AA64-30386D	CABINET-BACK;-,5339,-,HIPS,V2,BLK,-,-	
	AA65-30107A	CLAMP-D,COIL;NYLON 66,V2,NTR,-,20~22 INCH,-	
		ASSY-CRT	
⚠	AA03-10024T	CRT-COLOR;-,A51KQJ63X(H),+380mG,21,90de	
	AA27-00002A	MAGNET-CONVERGENCE;-,JH291-SC-OB,29.1MM	
⚠	AA27-50004K	DEFLECTION-YOKE;	
		ASSY ACCESSORY	
	AA63-00261B	COVER-JACK;-,2139,BK708P,HIPS,HB,G4309,-,-	
		REMOCON	
*	AA59-00104C	REMOCON;-,TM59,8IM806E,29,L/GRAY,PAL-MONO, TTX,-,-,- ,-,-	

7-7 CS2139TX/BWT(CS1448X/BWT and CS2139TX/BWT Dissimilar Parts)

Loc. No.	Code No.	Description ; Specification	Remark
		ASSY PCB MAIN(OPT)	
*	AA94-02295A	ASSY PCB MAIN(OPT);CS2139TR6X/BWT,KS1A,CIS,-	
CN603	3711-002643	CONNECTOR-HEADER;BOX,4P,1R,2.5mm,STRAIGHT,SN	
CR402S	2306-000188	C-FILM,MPPF;330nF,5%,400V,TP,26x19.5x11,20	
CR410S	2306-000327	C-FILM,MPPF;6.3nF,3%,1.6KV,TP,28.5x18x10,2	
⚠ IC201S	AA09-00022A	IC-MCU;TDA9351/4-OTP,TDA9351/4,ST,- ,64,SDIP,12KHz,8,6048,1uS,-,CMOS,-,8,PUS,-,MCU,750,3	
L403	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
LC801S	AA27-20004A	COIL-DEGAUSSING;-,21,14ohm,45T,L2380,E	
R302	2004-004366	R-METAL(S);1.3Kohm,1%,1/2W,AA,TP,2.5x6.5m	
R306	2004-001369	R-METAL(S);1.2Kohm,1%,1/2W,AA,TP,2.4x6.4m	
R315	2003-002009	R-METAL OXIDE(S);390ohm,5%,2W,AF,TP,3.9x10mm	
R316	2003-002009	R-METAL OXIDE(S);390ohm,5%,2W,AF,TP,3.9x10mm	
R405	2001-001116	R-CARBON(S);27OHM,5%,1/2W,AA,TP,2.4X6.4MM	
R501H	2002-001008	R-COMPOSITION;1.8Kohm,10%,1/2W,AA,TP,3.7x9mm	
R502H	2002-001008	R-COMPOSITION;1.8Kohm,10%,1/2W,AA,TP,3.7x9mm	
R601	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R814	2008-001116	R-FUSIBLE(S);0.68ohm,10%,2W,AG,TP,3.9x12mm	
R815	2008-001116	R-FUSIBLE(S);0.68ohm,10%,2W,AG,TP,3.9x12mm	
⚠ V999S	3704-001105	SOCKET-CRT;11P,20PI,26.5PI,NI,-	
		ASSY CABINET FRONT	
*	AA91-00086L	ASSY CABINET FRONT;-,2139,(SPK)BK708 PROGUN I I,HB,BLK	
CABBAC	AA63-60001L	SPACER-FELT;FELT,T0.35,BLK,150X15,-,-	
CB+CF	6002-000514	SCREW-TAPPING;RH,+,2,M4,L15,ZPC(BLK),SWRCH18	
CB+RCA	6002-000514	SCREW-TAPPING;RH,+,2,M4,L15,ZPC(BLK),SWRCH18	
CRT+CF	AA60-10050R	SCREW-ASSY;WC,HH,+,M5,L31.5,SWRCH18A,ZPC(	
KNPOMA	AA61-60003J	SPRING-CS;-,SUS304,0.5,OD6,H12,N7,-,-,-	
PA+CF	AA60-10002A	SCREW-TAPPING;RH,+,M4,L12,ZPC(YEL),-,OD14	
SPK+CF	6003-001026	SCREW-TAPTITE;RH,+,B,M4,L15,ZPC(BLK),SWRCH18	
	AA63-50053B	GRILLE-WOOFER;-,5339,PA110,SECC,T0.5,-,-	
	AA64-00236L	CABINET FRONT;-,5339,BK708P CIS PROGUN II,HIPS,HB,BLK,-,-	
	AA61-40015A	BOSS-CABINET;-,HIPS,HB,NTR,-,-	
	AA64-10014A	KNOB-CONTROL;-,5339,-,ABS,HB,BLK	
	AA64-10185A	KNOB-POWER,M;-,5339,-,ABS,HB,BLK	
	AA64-40053A	WINDOW-REMOCON;-,5339,-,PC,V0,VIOLET,-	
	AA64-40186A	INDICATOR-LED;-,5339,-,ACRYL,-,-,-	
	AA64-70123B	BADGE-BRAND;AL,R2000,SILVER,L=50,SAMSUNG,-	
	AA96-10137B	ASSY-SPEAKER;-,8OHM,3W,3001-001020,AA39-20505M,R700/L350	
	3001-001020	SPEAKER;3W,8ohm,90dB,140Hz	
	AA39-20505M	LEAD CONNECTOR-ASSY;-,YSH025-04,REC,4P,350,700mm,1	
	AA64-30386D	CABINET-BACK;-,5339,-,HIPS,V2,BLK,-,-	
	AA65-30107A	CLAMP-D,COIL;NYLON 66,V2,NTR,-,20~22 INCH,-	
		ASSY-CRT	
⚠	AA03-10024T	CRT-COLOR;-,A51KQJ63X(H),+380mG,21,90de	
	AA27-00002A	MAGNET-CONVERGENCE;-,JH291-SC-OB,29.1MM	
⚠	AA27-50004K	DEFLECTION-YOKE;	
		ASSY ACCESSORY	
	AA63-00261B	COVER-JACK;-,2139,BK708P,HIPS,HB,G4309,-,-	
		REMOCON	
*	AA59-00104C	REMOCON;-,TM59,8IM806E,29,L/GRAY,PAL-MONO, TTX,-,-,-,-,-	

7-8 CS2139X/BWT(CS1448X/BWT and CS2139X/BWT Dissimilar Parts)

Loc. No.	Code No.	Description ; Specification	Remark

ASSY PCB MAIN(OPT)

*	AA94-02066T	ASSY PCB MAIN(OPT);CS2139X/BWT,KS1A,RUSSIA,-	
CN603	3711-002643	CONNECTOR-HEADER;BOX,4P,1R,2.5mm,STRAIGHT,SN	
CR402S	2306-000188	C-FILM,MPPF;330nF,5%,400V,TP,26x19.5x11,20	
CR410S	2306-000327	C-FILM,MPPF;6.3nF,3%,1.6KV,TP,28.5x18x10,2	
L403	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
LC801S	AA27-20004A	COIL-DEGAUSSING;-,21,14ohm,45T,L2380,E	
R302	2004-004366	R-METAL(S);1.3Kohm,1%,1/2W,AA,TP,2.5x6.5m	
R306	2004-001369	R-METAL(S);1.2Kohm,1%,1/2W,AA,TP,2.4x6.4m	
R315	2003-002009	R-METAL OXIDE(S);390ohm,5%,2W,AF,TP,3.9x10mm	
R316	2003-002009	R-METAL OXIDE(S);390ohm,5%,2W,AF,TP,3.9x10mm	
R405	2001-001116	R-CARBON(S);27OHM,5%,1/2W,AA,TP,2.4X6.4MM	
R501H	2002-001008	R-COMPOSITION;1.8Kohm,10%,1/2W,AA,TP,3.7x9mm	
R502H	2002-001008	R-COMPOSITION;1.8Kohm,10%,1/2W,AA,TP,3.7x9mm	
R601	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R814	2008-001116	R-FUSIBLE(S);0.68ohm,10%,2W,AG,TP,3.9x12mm	
R815	2008-001116	R-FUSIBLE(S);0.68ohm,10%,2W,AG,TP,3.9x12mm	
⚠ V999S	3704-001105	SOCKET-CRT;11P,20PI,26.5PI,NI,-	

ASSY CABINET FRONT

*	AA91-00086L	ASSY CABINET FRONT;-,2139,(SPK)BK708 PROGUN II,HB,BLK	
CABBAC	AA63-60001L	SPACER-FELT;FELT,T0.35,BLK,150X15,-,-	
CB+CF	6002-000514	SCREW-TAPPING;RH,+,2,M4,L15,ZPC(BLK),SWRCH18	
CB+RCA	6002-000514	SCREW-TAPPING;RH,+,2,M4,L15,ZPC(BLK),SWRCH18	
CRT+CF	AA60-10050R	SCREW-ASSY;WC,HH,+,M5,L31.5,SWRCH18A,ZPC(	
KNPOMA	AA61-60003J	SPRING-CS;-,SUS304,0.5,OD6,H12,N7,-,-,-	
PA+CF	AA60-10002A	SCREW-TAPPING;RH,+,M4,L12,ZPC(YEL),-,OD14	
SPK+CF	6003-001026	SCREW-TAPTITE;RH,+,B,M4,L15,ZPC(BLK),SWRCH18	
	AA63-50053B	GRILLE-WOOFER;-,5339,PA110,SECC,T0.5,-,-	
	AA64-00236L	CABINET FRONT;-,5339,BK708P CIS PROGUN II,HIPS,HB,BLK,-,-	
	AA61-40015A	BOSS-CABINET;-,HIPS,HB,NTR,-,-	
	AA64-10014A	KNOB-CONTROL;-,5339,-,ABS,HB,BLK	
	AA64-10185A	KNOB-POWER,M;-,5339,-,ABS,HB,BLK	
	AA64-40053A	WINDOW-REMOCON;-,5339,-,PC,V0,VIOLET,-	
	AA64-40186A	INDICATOR-LED;-,5339,-,ACRYL,-,-,-	
	AA64-70123B	BADGE-BRAND;AL,R2000,SILVER,L=50,SAMSUNG,-	
	AA96-10137B	ASSY-SPEAKER;-,8OHM,3W,3001-001020,AA39-20505M,R700/L350	
	3001-001020	SPEAKER;3W,8ohm,90dB,140Hz	
	AA39-20505M	LEAD CONNECTOR-ASSY;-,YSH025-04,REC,4P,350,700mm,1	
	AA64-30386D	CABINET-BACK;-,5339,-,HIPS,V2,BLK,-,-	
	AA65-30107A	CLAMP-D,COIL;NYLON 66,V2,NTR,-,20~22 INCH,-	

ASSY-CRT

⚠	AA03-10024T	CRT-COLOR;-,A51KQJ63X(H),+380mG,21,90de	
	AA27-00002A	MAGNET-CONVERGENCE;-,JH291-SC-OB,29.1MM	
⚠	AA27-50004K	DEFLECTION-YOKE;	

ASSY ACCESSORY

	AA63-00261B	COVER-JACK;-,2139,BK708P,HIPS,HB,G4309,-,-	

REMOCON

*	AA59-00104D	REMOCON;-,TM59,SIM806E,24,L/GRAY,-,PAL-MONO,-,-,-,-	

7-9 CS2139X/NWT(CS1448X/BWT and CS2139X/NWT Dissimilar Parts)

Loc. No.	Code No.	Description ; Specification	Remark

ASSY PCB MAIN(OPT)

*	AA94-02069X	ASSY PCB MAIN(OPT);CS2139X/NWT,KS1A,UKRAINE,-	
CN603	3711-002643	CONNECTOR-HEADER;BOX,4P,1R,2.5mm,STRAIGHT,SN	
CR402S	2306-000188	C-FILM,MPPF;330nF,5%,400V,TP,26x19.5x11,20	
CR410S	2306-000327	C-FILM,MPPF;6.3nF,3%,1.6KV,TP,28.5x18x10,2	
L403	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
LC801S	AA27-20004A	COIL-DEGAUSSING;-,21,14ohm,45T,L2380,E	
R302	2004-004366	R-METAL(S);1.3Kohm,1%,1/2W,AA,TP,2.5x6.5m	
R306	2004-001369	R-METAL(S);1.2Kohm,1%,1/2W,AA,TP,2.4x6.4m	
R315	2003-002009	R-METAL OXIDE(S);390ohm,5%,2W,AF,TP,3.9x10mm	
R316	2003-002009	R-METAL OXIDE(S);390ohm,5%,2W,AF,TP,3.9x10mm	
R405	2001-001116	R-CARBON(S);27OHM,5%,1/2W,AA,TP,2.4X6.4MM	
R501H	2002-001008	R-COMPOSITION;1.8Kohm,10%,1/2W,AA,TP,3.7x9mm	
R502H	2002-001008	R-COMPOSITION;1.8Kohm,10%,1/2W,AA,TP,3.7x9mm	
R601	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R814	2008-001116	R-FUSIBLE(S);0.68ohm,10%,2W,AG,TP,3.9x12mm	
R815	2008-001116	R-FUSIBLE(S);0.68ohm,10%,2W,AG,TP,3.9x12mm	
⚠ V999S	3704-001105	SOCKET-CRT;11P,20PI,26.5PI,NI,-	

ASSY CABINET FRONT

*	AA91-00086L	ASSY CABINET FRONT;-,2139,(SPK)BK708 PROGUN II,HB,BLK	
CABBAC	AA63-60001L	SPACER-FELT;FELT,T0.35,BLK,150X15,-,-	
CB+CF	6002-000514	SCREW-TAPPING;RH,+,2,M4,L15,ZPC(BLK),SWRCH18	
CB+RCA	6002-000514	SCREW-TAPPING;RH,+,2,M4,L15,ZPC(BLK),SWRCH18	
CRT+CF	AA60-10050R	SCREW-ASSY;WC,HH,+,M5,L31.5,SWRCH18A,ZPC(	
KNPOMA	AA61-60003J	SPRING-CS;-,SUS304,0.5,OD6,H12,N7,-,-,-	
PA+CF	AA60-10002A	SCREW-TAPPING;RH,+,M4,L12,ZPC(YEL),-,OD14	
SPK+CF	6003-001026	SCREW-TAPTITE;RH,+,B,M4,L15,ZPC(BLK),SWRCH18	
	AA63-50053B	GRILLE-WOOFER;-,5339,PA110,SECC,T0.5,-,-	
	AA64-00236L	CABINET FRONT;-,5339,BK708P CIS PROGUN II,HIPS,HB,BLK,-,-	
	AA61-40015A	BOSS-CABINET;-,HIPS,HB,NTR,-,-	
	AA64-10014A	KNOB-CONTROL;-,5339,-,ABS,HB,BLK	
	AA64-10185A	KNOB-POWER,M;-,5339,-,ABS,HB,BLK	
	AA64-40053A	WINDOW-REMOCON;-,5339,-,PC,V0,VIOLET,-	
	AA64-40186A	INDICATOR-LED;-,5339,-,ACRYL,-,-,-	

Loc. No.	Code No.	Description ; Specification	Remark
	AA64-70123B	BADGE-BRAND;AL,R2000,SILVER,L=50,SAMSUNG,-	
	AA96-10137B	ASSY-SPEAKER;-,8OHM,3W,3001-001020,AA39-20505M,R700/L350	
	3001-001020	SPEAKER;3W,8ohm,90dB,140Hz	
	AA39-20505M	LEAD CONNECTOR-ASSY;-,YSH025-04,REC,4P,350,700mm,1	
	AA64-30386D	CABINET-BACK;-,5339,-,HIPS,V2,BLK,-,-	
	AA65-30107A	CLAMP-D,COIL;NYLON 66,V2,NTR,-,20~22 INCH,-	
		ASSY-CRT	
⚠	AA03-10024T	CRT-COLOR;-,A51KQJ63X(H),+380mG,21,90de	
	AA27-00002A	MAGNET-CONVERGENCE;-,JH291-SC-OB,29.1MM	
⚠	AA27-50004K	DEFLECTION-YOKE;	
		ASSY ACCESSORY	
	AA63-00261B	COVER-JACK;-,2139,BK708P,HIPS,HB,G4309,-,-	
	AA68-01010A	MANUAL USERS;-,-,B5,-,W/P100(G),-,-,1,-,-,KS1A,TTX,32P,UKRAINE	

Loc. No.	Code No.	Description ; Specification	Remark
		REMOCON	
*	AA59-00104D	REMOCON;-,TM59,SIM806E,24,L/GRAY,-,PAL-MONO,-,-,-,-	

7-10 CS2139X/VWT(CS1448X/BWT and CS2139X/VWT Dissimilar Parts)

Loc. No.	Code No.	Description ; Specification	Remark
		ASSY PCB MAIN(OPT)	
*	AA94-02069E	ASSY PCB MAIN(OPT);CS2139X/VWT,KS1A,LITHUANIA,-	
CN603	3711-002643	CONNECTOR-HEADER;BOX,4P,1R,2.5mm,STRAIGHT,SN	
CR402S	2306-000188	C-FILM,MPPF;330nF,5%,400V,TP,26x19.5x11,20	
CR410S	2306-000327	C-FILM,MPPF;6.3nF,3%,1.6KV,TP,28.5x18x10,2	
L403	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
LC801S	AA27-20004A	COIL-DEGAUSSING;-,21,14ohm,45T,L2380,E	
R302	2004-004366	R-METAL(S);1.3Kohm,1%,1/2W,AA,TP,2.5x6.5m	
R306	2004-001369	R-METAL(S);1.2Kohm,1%,1/2W,AA,TP,2.4x6.4m	
R315	2003-002009	R-METAL OXIDE(S);390ohm,5%,2W,AF,TP,3.9x10mm	
R316	2003-002009	R-METAL OXIDE(S);390ohm,5%,2W,AF,TP,3.9x10mm	
R405	2001-001116	R-CARBON(S);27OHM,5%,1/2W,AA,TP,2.4X6.4MM	
R501H	2002-001008	R-COMPOSITION;1.8Kohm,10%,1/2W,AA,TP,3.7x9mm	
R502H	2002-001008	R-COMPOSITION;1.8Kohm,10%,1/2W,AA,TP,3.7x9mm	
R601	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R814	2008-001116	R-FUSIBLE(S);0.68ohm,10%,2W,AG,TP,3.9x12mm	
R815	2008-001116	R-FUSIBLE(S);0.68ohm,10%,2W,AG,TP,3.9x12mm	
⚠ V999S	3704-001105	SOCKET-CRT;11P,20PI,26.5PI,NI,-	
		ASSY CABINET FRONT	
*	AA91-00086L	ASSY CABINET FRONT;-,2139,(SPK)BK708 PROGUN II,HB,BLK	
CABBAC	AA63-60001L	SPACER-FELT;FELT,T0.35,BLK,150X15,-,-	
CB+CF	6002-000514	SCREW-TAPPING;RH,+,2,M4,L15,ZPC(BLK),SWRCH18	
CB+RCA	6002-000514	SCREW-TAPPING;RH,+,2,M4,L15,ZPC(BLK),SWRCH18	
CRT+CF	AA60-10050R	SCREW-ASSY;WC,HH,+,M5,L31.5,SWRCH18A,ZPC(	
KNPOMA	AA61-60003J	SPRING-CS;-,SUS304,0.5,OD6,H12,N7,-,-,-	
PA+CF	AA60-10002A	SCREW-TAPPING;RH,+,M4,L12,ZPC(YEL),-,OD14	
SPK+CF	6003-001026	SCREW-TAPTITE;RH,+,B,M4,L15,ZPC(BLK),SWRCH18	
	AA63-50053B	GRILLE-WOOFER;-,5339,PA110,SECC,T0.5,-,-	
	AA64-00236L	CABINET FRONT;-,5339,BK708P CIS PROGUN II,HIPS,HB,BLK,-,-	
	AA61-40015A	BOSS-CABINET;-,HIPS,HB,NTR,-,-	
	AA64-10014A	KNOB-CONTROL;-,5339,-,ABS,HB,BLK	
	AA64-10185A	KNOB-POWER,M;-,5339,-,ABS,HB,BLK	
	AA64-40053A	WINDOW-REMOCON;-,5339,-,PC,V0,VIOLET,-	

Loc. No.	Code No.	Description ; Specification	Remark
	AA64-40186A	INDICATOR-LED;-,5339,-,ACRYL,-,-,-	
	AA64-70123B	BADGE-BRAND;AL,R2000,SILVER,L=50,SAMSUNG,-	
	AA96-10137B	ASSY-SPEAKER;-,8OHM,3W,3001-001020,AA39-20505M,R700/L350	
	3001-001020	SPEAKER;3W,8ohm,90dB,140Hz	
	AA39-20505M	LEAD CONNECTOR-ASSY;-,YSH025-04,REC,4P,350,700mm,1	
	AA64-30386D	CABINET-BACK;-,5339,-,HIPS,V2,BLK,-,-	
	AA65-30107A	CLAMP-D,COIL;NYLON 66,V2,NTR,-,20~22 INCH,-	
		ASSY-CRT	
⚠	AA03-10024T	CRT-COLOR;-,A51KQJ63X(H),+380mG,21,90de	
	AA27-00002A	MAGNET-CONVERGENCE;-,JH291-SC-OB,29.1MM	
⚠	AA27-50004K	DEFLECTION-YOKE;	
		ASSY ACCESSORY	
	AA63-00261B	COVER-JACK;-,2139,BK708P,HIPS,HB,G4309,-,-	
		REMOCON	
*	AA59-00104D	REMOCON;-,TM59,SIM806E,24,L/GRAY,-,PAL-MONO,-,-,-,-	

7-11 CS2148X/NWT(CS1448X/BWT and CS2148X/NWT Dissimilar Parts)

Loc. No.	Code No.	Description ; Specification	Remark

ASSY PCB MAIN(OPT)

*	AA94-02069V	ASSY PCB MAIN(OPT);CS2148X/NWT,KS1A,UKRAINE,-	
CR402S	2306-000188	C-FILM,MPPF;330nF,5%,400V,TP,26x19.5x11,20	
CR410S	2306-000327	C-FILM,MPPF;6.3nF,3%,1.6KV,TP,28.5x18x10,2	
L403	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
LC801S	AA27-20004A	COIL-DEGAUSSING;-,21,14ohm,45T,L2380,E	
R302	2004-004366	R-METAL(S);1.3Kohm,1%,1/2W,AA,TP,2.5x6.5m	
R306	2004-001369	R-METAL(S);1.2Kohm,1%,1/2W,AA,TP,2.4x6.4m	
R315	2003-002009	R-METAL OXIDE(S);390ohm,5%,2W,AF,TP,3.9x10mm	
R316	2003-002009	R-METAL OXIDE(S);390ohm,5%,2W,AF,TP,3.9x10mm	
R405	2001-001116	R-CARBON(S);27OHM,5%,1/2W,AA,TP,2.4X6.4MM	
R501H	2002-001008	R-COMPOSITION;1.8Kohm,10%,1/2W,AA,TP,3.7x9mm	
R502H	2002-001008	R-COMPOSITION;1.8Kohm,10%,1/2W,AA,TP,3.7x9mm	
⚠ V999S	3704-001105	SOCKET-CRT;11P,20PI,26.5PI,NI,-	

ASSY CABINET FRONT

*	AA91-00089D	ASSY CABINET FRONT;-,5338,(SPK)MMP2,ABS V0,WHT	
CRT+CF	AA60-10050R	SCREW-ASSY;WC,HH,+,M5,L31.5,SWRCH18A,ZPC(	
KC+CF	6003-001019	SCREW-TAPTITE;RH,+,B,M4,L12,ZPC(BLK),SWRCH18	
KNOPOW	AA61-60003B	SPRING-CS;-,SUS304,0.7,OD11.2,H16,N7,-,-	
SPK+CF	6003-001026	SCREW-TAPTITE;RH,+,B,M4,L15,ZPC(BLK),SWRCH18	
	AA61-40007A	STOPPER-PCB;5038.5368,HIPS HB,-,NTR,-,-,-	
	AA63-50052B	GRILLE-WOOFER;-,5338,-,SECC,T0.5,WHT,-	
	AA64-10046B	KNOB-CONTROL;-,5338,-,ABS,V0,WHT	
	AA64-10140E	KNOB-POWER;-,5338,-,ABS,V0,WHT	
	AA64-30133R	CABINET FRONT;5338,MMP2,ABS,V0,WHT	
	AA64-40084B	WINDOW-REMOCON;-,5338,-,PC,VO,VIOLET,-	
	AA64-40185A	INDICATOR-LED;-,5338,-,ACRYL,-,-,-	
	AA96-10140B	ASSY-SPEAKER;-,16OHM,3W,3001-001039,AA39-20501C,-	
	3001-001039	SPEAKER;3W,16ohm,90dB,180Hz	
	AA39-20501C	LEAD CONNECTOR-ASSY;-,67096-003,REC,3(2)P,700mm,10	
	AA64-30710F	CABINET-BACK;-,5338,VE0812,ABS,V0, WHT,-,-	
	AA65-30107A	CLAMP-D,COIL;NYLON 66,V2,NTR,-,20~22 INCH,-	

Loc. No.	Code No.	Description ; Specification	Remark

ASSY-CRT

⚠	AA03-10024T	CRT-COLOR;-,A51KQJ63X(H),+380mG,21,90de	
	AA27-00002A	MAGNET-CONVERGENCE;-,JH291-SC-OB,29.1MM	
⚠	AA27-50004K	DEFLECTION-YOKE;	

ASSY ACCESSORY

	AA68-01010A	MANUAL USERS;-,-,B5,-,W/P100(G),-,-,1,-,- ,KS1A,TTX,32P,UKRAINE	

7-12 CS2148X/VWT(CS1448X/BWT and CS2148X/VWT Dissimilar Parts)

Loc. No.	Code No.	Description ; Specification	Remark

ASSY PCB MAIN(OPT)

*	AA94-02070R	ASSY PCB MAIN(OPT);CS2148X/VWT,KS1A,LITHUANIA,-	
CR402S	2306-000188	C-FILM,MPPF;330nF,5%,400V,TP,26x19.5x11,20	
CR410S	2306-000327	C-FILM,MPPF;6.3nF,3%,1.6KV,TP,28.5x18x10,2	
L403	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
LC801S	AA27-20004A	COIL-DEGAUSSING;-,21,14ohm,45T,L2380,E	
R302	2004-004366	R-METAL(S);1.3Kohm,1%,1/2W,AA,TP,2.5x6.5m	
R306	2004-001369	R-METAL(S);1.2Kohm,1%,1/2W,AA,TP,2.4x6.4m	
R315	2003-002009	R-METAL OXIDE(S);390ohm,5%,2W,AF,TP,3.9x10mm	
R316	2003-002009	R-METAL OXIDE(S);390ohm,5%,2W,AF,TP,3.9x10mm	
R405	2001-001116	R-CARBON(S);27OHM,5%,1/2W,AA,TP,2.4X6.4MM	
R501H	2002-001008	R-COMPOSITION;1.8Kohm,10%,1/2W,AA,TP,3.7x9mm	
R502H	2002-001008	R-COMPOSITION;1.8Kohm,10%,1/2W,AA,TP,3.7x9mm	
⚠ V999S	3704-001105	SOCKET-CRT;11P,20PI,26.5PI,NI,-	

Loc. No.	Code No.	Description ; Specification	Remark

ASSY CABINET FRONT

*	AA91-00089D	ASSY CABINET FRONT;-,5338,(SPK)MMP2,ABS V0,WHT	
CRT+CF	AA60-10050R	SCREW-ASSY;WC,HH,+,M5,L31.5,SWRCH18A,ZPC(	
KC+CF	6003-001019	SCREW-TAPTITE;RH,+,B,M4,L12,ZPC(BLK),SWRCH18	
KNOPOW	AA61-60003B	SPRING-CS;-,SUS304,0.7,OD11.2,H16,N7,-,-	
SPK+CF	6003-001026	SCREW-TAPTITE;RH,+,B,M4,L15,ZPC(BLK),SWRCH18	
	AA61-40007A	STOPPER-PCB;5038.5368,HIPS HB,-,NTR,-,-,-	
	AA63-50052B	GRILLE-WOOFER;-,5338,-,SECC,T0.5,WHT,-	
	AA64-10046B	KNOB-CONTROL;-,5338,-,ABS,V0,WHT	
	AA64-10140E	KNOB-POWER;-,5338,-,ABS,V0,WHT	
	AA64-30133R	CABINET FRONT;5338,MMP2,ABS,V0,WHT	
	AA64-40084B	WINDOW-REMOCON;-,5338,-,PC,VO,VIOLET,-	
	AA64-40185A	INDICATOR-LED;-,5338,-,ACRYL,-,-,-	
	AA96-10140B	ASSY-SPEAKER;-,16OHM,3W,3001-001039,AA39-20501C,-	

	3001-001039	SPEAKER;3W,16ohm,90dB,180Hz
	AA39-20501C	LEAD CONNECTOR-ASSY;-,67096-003,REC,3(2)P,700mm,10
	AA64-30710F	CABINET-BACK;-,5338,VE0812,ABS,V0, WHT,-,-
	AA65-30107A	CLAMP-D,COIL;NYLON 66,V2,NTR,-,20~22 INCH,-

ASSY-CRT

⚠	AA03-10024T	CRT-COLOR;-,A51KQJ63X(H),+380mG,21,90de
	AA27-00002A	MAGNET-CONVERGENCE;-,JH291-SC-OB,29.1MM
⚠	AA27-50004K	DEFLECTION-YOKE;

7-13 CS2148X/BWT(CS1448X/BWT and CS2148X/BWT Dissimilar Parts)

Loc. No.	Code No.	Description ; Specification	Remark

Loc. No.	Code No.	Description ; Specification	Remark

ASSY PCB MAIN(OPT)

*	AA94-02066R	ASSY PCB MAIN(OPT);CS2148X/BWT,KS1A,RUSSIA,-	
CR402S	2306-000188	C-FILM,MPPF;330nF,5%,400V,TP,26x19.5x11,20	
CR410S	2306-000327	C-FILM,MPPF;6.3nF,3%,1.6KV,TP,28.5x18x10,2	
L403	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
LC801S	AA27-20004A	COIL-DEGAUSSING;-,21,14ohm,45T,L2380,E	
R302	2004-004366	R-METAL(S);1.3Kohm,1%,1/2W,AA,TP,2.5x6.5m	
R306	2004-001369	R-METAL(S);1.2Kohm,1%,1/2W,AA,TP,2.4x6.4m	
R315	2003-002009	R-METAL OXIDE(S);390ohm,5%,2W,AF,TP,3.9x10mm	
R316	2003-002009	R-METAL OXIDE(S);390ohm,5%,2W,AF,TP,3.9x10mm	
R405	2001-001116	R-CARBON(S);27OHM,5%,1/2W,AA,TP,2.4X6.4MM	
R501H	2002-001008	R-COMPOSITION;1.8Kohm,10%,1/2W,AA,TP,3.7x9mm	
R502H	2002-001008	R-COMPOSITION;1.8Kohm,10%,1/2W,AA,TP,3.7x9mm	
⚠ V999S	3704-001105	SOCKET-CRT;11P,20PI,26.5PI,NI,-	

ASSY CABINET FRONT

*	AA91-00089D	ASSY CABINET FRONT;-,5338,(SPK)MMP2,ABS V0,WHT	
CRT+CF	AA60-10050R	SCREW-ASSY;WC,HH,+,M5,L31.5,SWRCH18A,ZPC(	
KC+CF	6003-001019	SCREW-TAPTITE;RH,+,B,M4,L12,ZPC(BLK),SWRCH18	
KNOPOW	AA61-60003B	SPRING-CS;-,SUS304,0.7,OD11.2,H16,N7,-,-	
SPK+CF	6003-001026	SCREW-TAPTITE;RH,+,B,M4,L15,ZPC(BLK),SWRCH18	
	AA61-40007A	STOPPER-PCB;5038.5368,HIPS HB,-,NTR,-,-,-	
	AA63-50052B	GRILLE-WOOFER;-,5338,-,SECC,T0.5,WHT,-	
	AA64-10046B	KNOB-CONTROL;-,5338,-,ABS,V0,WHT	
	AA64-10140E	KNOB-POWER;-,5338,-,ABS,V0,WHT	
	AA64-30133R	CABINET FRONT;5338,MMP2,ABS,V0,WHT	
	AA64-40084B	WINDOW-REMOCON;-,5338,-,PC,VO,VIOLET,-	
	AA64-40185A	INDICATOR-LED;-,5338,-,ACRYL,-,-,-	
	AA96-10140B	ASSY-SPEAKER;-,16OHM,3W,3001-001039,AA39-20501C,-	
	3001-001039	SPEAKER;3W,16ohm,90dB,180Hz	
	AA39-20501C	LEAD CONNECTOR-ASSY;-,67096-003,REC,3(2)P,700mm,10	
	AA64-30710F	CABINET-BACK;-,5338,VE0812,ABS,V0, WHT,-,-	
	AA65-30107A	CLAMP-D,COIL;NYLON 66,V2,NTR,-,20~22 INCH,-	

ASSY-CRT

⚠	AA03-10024T	CRT-COLOR;-,A51KQJ63X(H),+380mG,21,90de
	AA27-00002A	MAGNET-CONVERGENCE;-,JH291-SC-OB,29.1MM
⚠	AA27-50004K	DEFLECTION-YOKE;

7-14 CS1448X/BWT Parts List

Loc. No.	Code No.	Description ; Specification	Remark

ASSY PCB MAIN(OPT)

*	AA94-02066C	ASSY PCB MAIN(OPT);CS1448X/BWT,KS1A,RUSS	
C101	2401-001101	C-AL;330uF,20%,16V,GP,TP,8x11.5,5	
C103	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
C105	2202-000127	C-CERAMIC,MLC-AXIAL;10nF,+80-20%,25V,Y5V	
C106	2202-000127	C-CERAMIC,MLC-AXIAL;10nF,+80-20%,25V,Y5V	
C109	2301-000224	C-FILM,PEF;22nF,5%,50V,TP,7.4x3.9x13mm,5	
C110	2401-000962	C-AL;22uF,20%,50V,GP,TP,5x11,5	
C111	2202-000127	C-CERAMIC,MLC-AXIAL;10nF,+80-20%,25V,Y5V	
C114	2201-000611	C-CERAMIC,DISC;0.056nF,5%,50V,NP0,TP,7x3	
C115	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
C119	2401-000027	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
C120	2401-002075	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
C121	2305-000411	C-FILM,MPEF;470nF,5%,50V,TP,7.3x4.8x5.5m	
C203	2401-000914	C-AL;22uF,20%,16V,GP,TP,5x11,5	
C204	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
C205	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
C206	2401-002235	C-AL;10uF,20%,16V,GP,TP,5x11mm,5mm	
C207	2305-000411	C-FILM,MPEF;470nF,5%,50V,TP,7.3x4.8x5.5m	
C208	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
C209	2401-001840	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
C210	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
C211	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
C212	2401-000660	C-AL;2.2uF,20%,50V,GP,TP,5x11,5	
C213	2401-001840	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
C214	2401-003102	C-AL;100uF,20%,10V,GP,TP,5x11,5	
C215	2305-000289	C-FILM,MPEF;220nF,5%,63V,TP,-,5mm	
C216	2305-000289	C-FILM,MPEF;220nF,5%,63V,TP,-,5mm	
C217	2301-000342	C-FILM,PEF;2.2nF,5%,50V,TP,7.4x3.9x13mm,	
C218	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
C219	2401-000603	C-AL;1uF,20%,50V,GP,TP,5x11,5	
C220	2401-002235	C-AL;10uF,20%,16V,GP,TP,5x11mm,5mm	
C221	2401-000660	C-AL;2.2uF,20%,50V,GP,TP,5x11,5	
C222	2401-000758	C-AL;220nF,20%,50V,GP,TP,5x11,5	
C223	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
C224	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
C225	2309-000138	C-FILM,PE-PPF;100nF,5%,50V,TP,20x16x8.5,	
C226	2202-000829	C-CERAMIC,MLC-AXIAL;.82NF,10%,50V,Y5P,TP	
C227	2301-000445	C-FILM,PEF;4.7nF,5%,50V,TP,5.5x7x3mm,5mm	
C229	2401-001840	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
C230	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
C231	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
C233	2305-000289	C-FILM,MPEF;220nF,5%,63V,TP,-,5mm	
C234	2301-000342	C-FILM,PEF;2.2nF,5%,50V,TP,7.4x3.9x13mm,	
C248	2301-000445	C-FILM,PEF;4.7nF,5%,50V,TP,5.5x7x3mm,5mm	
C301	2305-000285	C-FILM,MPEF;220NF,5%,100V,TP,10.5X5.5X15	
C302	2201-000259	C-CERAMIC,DISC;0.18nF,10%,500V,Y5P,TP,5.	
C303	2201-000556	C-CERAMIC,DISC;0.47nF,10%,500V,Y5P,TP,5.	
C304	2401-002288	C-AL;470uF,20%,25V,WT,TP,10x20,5	
C305	2201-000556	C-CERAMIC,DISC;0.47nF,10%,500V,Y5P,TP,5.	
C306	2401-002288	C-AL;470uF,20%,25V,WT,TP,10x20,5	
C307	2401-000360	C-AL;100uF,20%,50V,GP,TP,8x11.5,5	
C308	2401-000360	C-AL;100uF,20%,50V,GP,TP,8x11.5,5	
C309	2301-000254	C-FILM,PEF;39nF,5%,50V,TP,7.5x3.5x6.5mm,	
C312	2305-000149	C-FILM,MPEF;100nF,5%,100V,TP,12x12.5x6.5	
C403	2401-000560	C-AL;1uF,20%,160V,GP,TP,6.3x11,5	
C406	2401-002619	C-AL;47uF,20%,25V,GP,TP,5x11,5	
C407	2301-000383	C-FILM,PEF;10nF,5%,50V,TP,6x7x3.2mm,5mm	
C408	2201-000599	C-CERAMIC,DISC;0.56nF,10%,500V,Y5P,TP,5.	
C420	2301-001065	C-FILM,MPPF;47nF,5%,630V,TP,19x15.5x7,7.	
C501	2201-000192	C-CERAMIC,DISC;0.01nF,0.25pF,500V,NP0,TP	
C502	2301-000213	C-FILM,PEF;220nF,5%,250V,TP,21.5x11,7.5	
C503	2201-002063	C-CERAMIC,DISC;10nF,+80-20%,3KV,Y5V,TP,1	
C504	2401-001232	C-AL;4.7uF,20%,250V,GP,TP,10x12.5,5	
C505	2202-000825	C-CERAMIC,MLC-AXIAL;680pF,10%,50V,Y5P,TP	
C506	2401-000430	C-AL;10uF,20%,250V,GP,TP,10x16mm,5m	
C601	2401-001998	C-AL;1000uF,20%,25V,GP,TP,10x20,5mm	
C602	2401-000603	C-AL;1uF,20%,50V,GP,TP,5x11,5	
C603	2401-000603	C-AL;1uF,20%,50V,GP,TP,5x11,5	
C605	2301-000192	C-FILM,PEF;1nF,5%,50V,TP,5.3x10mm,5mm	
C606	2301-000289	C-FILM,PEF;5.6nF,5%,50V,TP,7x6x3,5	
C702	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
C703	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
C704	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
C705	2401-001989	C-AL;4.7uF,20%,50V,BP,TP,5x11,5	
C706	2401-001989	C-AL;4.7uF,20%,50V,BP,TP,5x11,5	
C707	2301-000204	C-FILM,PEF;2.7nF,5%,50V,TP,7.4x3.9x13mm,	
C708	2401-000480	C-AL;10uF,20%,50V,GP,TP,5x11,5	
C709	2401-001513	C-AL;47uF,20%,16V,WT,TP,5x11,5	
C801	2401-003030	C-AL;220uF,20%,450V,GP,BK,30x35,10	
C802	2401-001192	C-AL;33uF,20%,50V,GP,TP,6.3x11,5	
C803	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
C804	2301-000224	C-FILM,PEF;22nF,5%,50V,TP,7.4x3.9x13mm,5	
C805	2301-000235	C-FILM,PEF;3.9nF,5%,50V,TP,6.5x3.0x5.5mm	
C806	2301-001342	C-FILM,PPF;1.5nF,5%,800V,TP,15x6.5x11.5m	
C810	2301-000192	C-FILM,PEF;1nF,5%,50V,TP,5.3x10mm,5mm	
C811	2201-000991	C-CERAMIC,DISC;0.56nF,10%,2kV,Y5P,TP,7.5	
C812	2401-000262	C-AL;100uF,20%,160V,HR,TP,16x25,7.5	
C813	2401-002290	C-AL;47uF,20%,160V,GP,TP,13x20,5	
C814	2201-000991	C-CERAMIC,DISC;0.56nF,10%,2kV,Y5P,TP,7.5	
C815	2401-002215	C-AL;2200uF,20%,25V,WT,TP,13x25,5	
C816	2201-000375	C-CERAMIC,DISC;0.22nF,5%,50V,RH,TP,12.5x	
C817	2401-000302	C-AL;100uF,20%,25V,GP,TP,6.3x11,5	
C818	2401-003028	C-AL;100uF,20%,25V,WT,TP,6.3x11,5	
C819	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
C820	2401-000493	C-AL;10uF,20%,50V,LZ,TP,5x11mm,5mm	
C821	2401-000302	C-AL;100uF,20%,25V,GP,TP,6.3x11,5	
C823	2401-000302	C-AL;100uF,20%,25V,GP,TP,6.3x11,5	
C825	2401-000302	C-AL;100uF,20%,25V,GP,TP,6.3x11,5	
C827	2401-000927	C-AL;22uF,20%,250V,GP,TP,13x20,5	
C901	2305-000411	C-FILM,MPEF;470nF,5%,50V,TP,7.3x4.8x5.5m	
C903	2401-001840	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
C904	2201-000179	C-CERAMIC,DISC;10nF,10%,50V,Y5V,TP,6.5x3	
C906	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
C908	2201-000573	C-CERAMIC,DISC;0.047nF,5%,50V,NP0,TP,5x3	
C909	2201-000573	C-CERAMIC,DISC;0.047nF,5%,50V,NP0,TP,5x3	
C910	2401-001840	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
C911	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
C912	2202-000127	C-CERAMIC,MLC-AXIAL;10nF,+80-20%,25V,Y5V	
C913	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
C915	2401-001840	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
C916	2201-000193	C-CERAMIC,DISC;0.01nF,0.25pF,50V,NP0,TP,	
CN501	AA39-20620C	LEAD CONNECTOR-ASSY;-,-,-,9P,-,-,-,YBNH2	
CN601	3711-002642	CONNECTOR-HEADER;BOX,3P,1R,2.5MM,STRAIGH	
CN703	3711-002648	CONNECTOR-HEADER;BOX,9P,1R,2.5mm,STRAIGH	
CR402S	2306-000195	C-FILM,MPPF;360nF,5%,400V,TP,26x19x11.5,	
CR404S	2201-000639	C-CERAMIC,DISC;0.68nF,10%,2kV,Y5P,TP,9x5	
CR405S	2305-000382	C-FILM,MPEF;4.7nF,5%,400V,TP,-,5mm	
CR409S	2201-000406	C-CERAMIC,DISC;0.27nF,10%,2kV,Y5P,TP,6.3	
CR410S	2303-001015	C-FILM,PPF;5.5nF,5%,1.6kV,TP,29x9.5x17,2	
CX801S	2306-000318	C-FILM,MPPF;220nF,20%,250V,TP,-,22.5mm	
CY801S	2201-000446	C-CERAMIC,DISC;3.3nF,20%,400V,Y5U,TP,15x	
D201	0401-000005	DIODE-SWITCHING;1N4148,100V,200MA,DO-35,	
D301	0402-001105	DIODE-RECTIFIER;ERB43-04SV1,400V,1.0A,-,	
D302	0402-001352	DIODE-RECTIFIER;GUF15G-20A,400V,1.5A,DO-	
D303	0402-000132	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	
D304	0402-001105	DIODE-RECTIFIER;ERB43-04SV1,400V,1.0A,-,	
D305	0401-000005	DIODE-SWITCHING;1N4148,100V,200MA,DO-35,	
D307	0401-000005	DIODE-SWITCHING;1N4148,100V,200MA,DO-35,	
D401	0402-001105	DIODE-RECTIFIER;ERB43-04SV1,400V,1.0A,-,	
D501	0402-000254	DIODE-RECTIFIER;RGP10J,600V,1A,DO-41,TP	
D502	0402-001105	DIODE-RECTIFIER;ERB43-04SV1,400V,1.0A,-,	
D503	0402-001105	DIODE-RECTIFIER;ERB43-04SV1,400V,1.0A,-,	
D504	0402-001105	DIODE-RECTIFIER;ERB43-04SV1,400V,1.0A,-,	
D601	0401-000005	DIODE-SWITCHING;1N4148,100V,200MA,DO-35,	
D602	0401-000005	DIODE-SWITCHING;1N4148,100V,200MA,DO-35,	
⚠ D801S	0402-000213	DIODE-RECTIFIER;ERB12-06,600V,1.0A,DO-41	
⚠ D802	0402-001111	DIODE-RECTIFIER;1N5397GP,600V,1.5A,DO-20	
⚠ D802S	0402-000213	DIODE-RECTIFIER;ERB12-06,600V,1.0A,DO-41	
⚠ D803	0402-000254	DIODE-RECTIFIER;RGP10J,600V,1A,DO-41,TP	

Loc. No.	Code No.	Description ; Specification	Remark
⚠D803S	0402-000213	DIODE-RECTIFIER;ERB12-06,600V,1.0A,DO-41	
⚠D804	0401-000005	DIODE-SWITCHING;1N4148,100V,200MA,DO-35,	
⚠D804S	0402-000213	DIODE-RECTIFIER;ERB12-06,600V,1.0A,DO-41	
⚠D805	0402-000540	DIODE-RECTIFIER;RU20A,600V,1.5A,-,TP	
⚠D806	0402-001374	DIODE-RECTIFIER;SDS06U20S,200V,6A,TO-220	H/SINK
⚠D808	0401-000005	DIODE-SWITCHING;1N4148,100V,200MA,DO-35,	
⚠D809	0402-000132	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	
⚠D811	0401-000005	DIODE-SWITCHING;1N4148,100V,200MA,DO-35,	
⚠D812	0402-001105	DIODE-RECTIFIER;ERB43-04SV1,400V,1.0A,-,	
D902	0401-000005	DIODE-SWITCHING;1N4148,100V,200MA,DO-35,	
DZ101	0403-000700	DIODE-ZENER;TZP33A,33V,31-35V,1W,DO-41,T	
DZ201	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
DZ202	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
DZ203	0403-001322	DIODE-ZENER;MTZJ8.2B,7.78-8.19V,500mW,DO	
DZ204	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
DZ205	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
DZ206	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
DZ207	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
DZ301	0403-001328	DIODE-ZENER;MTZJ22A,20.15-21.20V,500mW,D	
DZ302	0403-001221	DIODE-ZENER;UZ39BSB,35.36-37.19V,500MW,D	
DZ303	0403-000700	DIODE-ZENER;TZP33A,33V,31-35V,1W,DO-41,T	
DZ305	0403-001328	DIODE-ZENER;MTZJ22A,20.15-21.20V,500mW,D	
DZ401	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
DZ402	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
DZ501	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
DZ502	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
DZ503	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
DZ504	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
DZ505	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
DZ506	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
DZ507	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
DZ601	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
DZ607	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
DZ701	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
DZ702	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
DZ703	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
DZ704	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
DZ801	0403-001140	DIODE-ZENER;RD10ESAB-T4,10V,9.19-10.30V,	
DZ802	0403-001318	DIODE-ZENER;MTZJ4.3B,4.17-4.43V,500mW,DO	
DZ803	0403-000699	DIODE-ZENER;TZP27B,27V,27-30.8V,1W,DO-41	
DZ805	0403-001327	DIODE-ZENER;MTZJ18A,16.22-17.06V,500mW,D	
DZ806	0403-001317	DIODE-ZENER;MTZJ3.0B,3.01-3.22V,500mW,DO	
DZ807	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
DZ808	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
DZ809	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
DZ810	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
DZ901	0403-001319	DIODE-ZENER;MTZJ4.7C,4.68-4.93V,500mW,DO	
DZ902	0403-000719	DIODE-ZENER;MTZJ7.5B,7.5V,7.07-7.45V,500	
DZ903	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
DZ904	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
DZ905	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
DZ908	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
F801A	3602-000114	FUSE-HOLDER;-,-,30mohm	
F801B	3602-000114	FUSE-HOLDER;-,-,30mohm	
⚠FD801S	3601-001086	FUSE-AXIAL LEAD;125V,5A,FAST-ACTING,GLAS	
⚠FP801S	3601-000281	FUSE-CARTRIDGE;250V,4A,TIME-LAG,GLASS,5.	
⚠IC101	1204-001583	IC-IF CIRCUIT;U4468B,DIP,16P,-,PLASTIC,5	
⚠IC201S	AA09-00025A	IC-MCU;TDA9381/3-OTP,TDA9381/3,ST,-,6	
⚠IC301	1204-001483	IC-VERTICAL PROCESSO;LA7840,SIP,7P,708MI	H/SINK
⚠IC501	1201-001159	IC-VIDEO AMP;6107,ZSIP,9P,-,SINGLE,-,PLA	H/SINK
⚠IC601	1201-001308	IC-POWER AMP;7266,ZIP,15P,-,DUAL,26dB,PL	H/SINK
⚠IC801S	1203-001932	IC-PWM CONTROLLER;5Q0765,TO-220F,5P,185M	H/SINK
⚠IC802	1203-001939	IC-POSI.FIXED REG.;7632,SIP,10P,-,PLASTI	H/SINK
⚠IC803	1203-001217	IC-POSI.ADJUST REG.;431,TO-92,3P,4.58MIL	
⚠IC902	1103-001106	IC-EEPROM;24C080,1028x8BIT,DIP,8P,300MIL	
J137	2001-000869	R-CARBON;56OHM,5%,1/8W,AA,TP,1.8X3.2MM	
J184	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
J910	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
JS701	3722-000497	JACK-PIN;4P,3.4MM,SN,BLK,-	
L102	2701-000159	INDUCTOR-AXIAL;22uH,10%,4.2x9.8mm	
L103	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
L104	2701-000168	INDUCTOR-AXIAL;3.3uH,5%,2.5x3.4mm	
L201	2701-000159	INDUCTOR-AXIAL;22uH,10%,4.2x9.8mm	
L202	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
L204	2701-000169	INDUCTOR-AXIAL;3.9uH,10%,2.5x3.4mm	
L205	2701-000159	INDUCTOR-AXIAL;22uH,10%,4.2x9.8mm	
L301	2701-000142	INDUCTOR-AXIAL;1uH,10%,2.5x3.4mm	
L302	2701-000142	INDUCTOR-AXIAL;1uH,10%,2.5x3.4mm	
L404	2701-000142	INDUCTOR-AXIAL;1uH,10%,2.5x3.4mm	
L405	2701-000159	INDUCTOR-AXIAL;22uH,10%,4.2x9.8mm	
L702	2701-000184	INDUCTOR-AXIAL;4.7uH,10%,2.5x3.4mm	
L703	2701-000184	INDUCTOR-AXIAL;4.7uH,10%,2.5x3.4mm	
L704	2701-000184	INDUCTOR-AXIAL;4.7uH,10%,2.5x3.4mm	
L706	2701-000184	INDUCTOR-AXIAL;4.7uH,10%,2.5x3.4mm	
L802	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
L803	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
L805	AA27-10002L	COIL-CHOKE;-,24UH,K,-,2A,-,24UH-K,10X10M	
L806	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
L808	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
L901	2701-000211	INDUCTOR-AXIAL;68uH,10%,2.5x3.4mm	
L902	2701-000180	INDUCTOR-AXIAL;33uH,5%,2.5x3.4mm	
L903	2701-000158	INDUCTOR-AXIAL;22uH,10%,2.5x3.4mm	
L904	2701-000180	INDUCTOR-AXIAL;33uH,5%,2.5x3.4mm	
L910	2701-000158	INDUCTOR-AXIAL;22uH,10%,2.5x3.4mm	
LC801S	AA27-20003U	COIL-DEGAUSSING;-,14,16.4ohm,75T,890mm,D	
LD901	AA96-30007A	ASSY-LED,GUIDE;-,AA61-50055A,DL-G7GA,GRE	
LR401S	AA27-00053A	COIL-LINEARLITY;-,193uH,DR10X10 C:4.35,7	
LX801S	AA29-30001D	FILTER-LINE NOISE;SQ1913,-,6.0MH,0.8A,-	
NT802S	1404-001045	THERMISTOR-NTC;4.7OHM,15%,2900K,35.0MW,T	
P803S	1404-001156	THERMISTOR-PTC;9OHM,+30%/-20%,220VRMS,27	
PC801S	0604-001038	PHOTO-COUPLER;TR,130-260%,200mW,DIP-4,ST	
PCB	AA41-00131B	PCB-MAIN;CS2139TC,FR-1,1L,B,1.6T,245x24	
Q201	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
Q202	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
Q205	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
Q206	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
Q301	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
⚠Q401	0502-001160	TR-POWER;2SD2499,NPN,50000mW,TO-3P,BK,8	
⚠Q402	0501-000369	TR-SMALL SIGNAL;KSC2331-Y,NPN,1W,TO-92L,	
Q701	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
Q702	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
Q703	0504-000123	TR-DIGITAL;KSR1010,NPN,300mW,10K,TO-92,T	
⚠Q802	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
⚠Q803	0502-000242	TR-POWER;KSA614,PNP,25W,TO-220,TP,40-24	
Q901	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
Q902	0504-000123	TR-DIGITAL;KSR1010,NPN,300mW,10K,TO-92,T	
Q904	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
R101	2001-000554	R-CARBON;270OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R102	2001-000554	R-CARBON;270OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R108	2001-000947	R-CARBON;7.5KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R109	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R110	2001-000924	R-CARBON;680OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R115	2001-000645	R-CARBON;330KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R116	2001-000319	R-CARBON;120KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R117	2001-000924	R-CARBON;680OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R202	2001-000689	R-CARBON;390KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R203	2001-000857	R-CARBON;560OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R204	2001-000857	R-CARBON;560OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R205	2001-000011	R-CARBON;75KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R206	2001-000563	R-CARBON;27KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R207	2001-000005	R-CARBON;390ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R208	2001-000591	R-CARBON;3.3KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R209	2001-000793	R-CARBON;47OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R211	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R213	2001-000938	R-CARBON;68OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R214	2001-000490	R-CARBON;200OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R215	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R218	2001-000008	R-CARBON;15KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R219	2004-001914	R-METAL;39Kohm,2%,1/8W,AA,TP,1.8x3.5mm	
R220	2001-000472	R-CARBON;2.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R222	2001-000947	R-CARBON;7.5KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R223	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R224	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R225	2001-000309	R-CARBON;110OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R227	2001-000739	R-CARBON;4.7MOHM,5%,1/8W,AA,TP,1.8X3.2M	
R228	2001-000739	R-CARBON;4.7MOHM,5%,1/8W,AA,TP,1.8X3.2M	
R229	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R230	2001-000924	R-CARBON;680OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R301	2001-000016	R-CARBON(S);1OHM,5%,1/2W,AA,TP,2.4X6.4MM	
R302	2004-001390	R-METAL(S);1Kohm,2%,1/2W,AA,TP,2.4x6.4mm	
R303	2003-002070	R-METAL OXIDE;1ohm,5%,2W,AF,TP,3.9x10mm	
R304	2008-000253	R-FUSIBLE(S);0.47ohm,5%,1W,AF,TP,3.9x10m	
R305	2008-000253	R-FUSIBLE(S);0.47ohm,5%,1W,AF,TP,3.9x10m	
R306	2004-001390	R-METAL(S);1Kohm,2%,1/2W,AA,TP,2.4x6.4mm	

Loc. No.	Code No.	Description ; Specification	Remark
R307	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R308	2001-001093	R-CARBON(S);2.2KOHM,5%,1/2W,AA,TP,2.4X6.	
R313	2001-000258	R-CARBON;1.8KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R314	2001-001088	R-CARBON(S);1KOHM,5%,1/2W,AA,TP,2.4X6.4M	
R316	2003-000652	R-METAL OXIDE(S);330ohm,5%,2W,AF,TP,4x12	
R402	2003-002178	R-METAL OXIDE(S);1Kohm,5%,2W,AG,TP,3.9x1	
R403	2003-000784	R-METAL OXIDE(S);7.5Kohm,5%,2W,AF,TP,4x1	
R405	2001-001195	R-CARBON(S);82OHM,5%,1/2W,AA,TP,2.4X6.4M	
R407	2003-002209	R-METAL OXIDE(S);47Kohm,5%,2W,AG,TP,3.9X	
R408	2001-001037	R-CARBON(S);0.39OHM,5%,1/2W,AA,TP,2.4X6.	
R409	2001-000022	R-CARBON(S);33OHM,5%,1/2W,AA,TP,2.4X6.4M	
R411	2001-001114	R-CARBON(S);270OHM,5%,1/2W,AA,TP,2.4X6.4	
R413	2003-000532	R-METAL OXIDE(S);18ohm,5%,2W,AF,TP,4x12m	
R414	2001-001078	R-CARBON(S);15KOHM,5%,1/2W,AA,TP,2.4X6.4	
R420	2008-001110	R-FUSIBLE(S);68ohm,5%,2W,AG,TP,3.9X12mm	
R421	2008-001114	R-FUSIBLE(S);1.5ohm,5%,2W,AG,TP,3.9x12mm	
R423	2004-001373	R-METAL(S);100Kohm,1%,1/2W,AA,TP,2.4x6.4	
R424	2004-001402	R-METAL(S);6.8Kohm,1%,1/2W,AA,TP,2.4x6.4	
R501	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R501M	2002-001008	R-COMPOSITION;1.8Kohm,10%,1/2W,AA,TP,3.7	
R502	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R502M	2002-001008	R-COMPOSITION;1.8Kohm,10%,1/2W,AA,TP,3.7	
R503	2002-001008	R-COMPOSITION;1.8Kohm,10%,1/2W,AA,TP,3.7	
R504	2001-001062	R-CARBON(S);10MOHM,5%,1/2W,AA,TP,2.4X6.4	
R505	2008-001011	R-FUSIBLE(S);0.18ohm,10%,2W,AF,TP,3.9x10	
R506	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R510	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R511	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R512	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R601	2001-000947	R-CARBON;7.5KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R602	2001-001015	R-CARBON;9.1KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R701	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R702	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R704	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R706	2001-000221	R-CARBON;1.2KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R708	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R710	2001-000004	R-CARBON;200KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R713	2001-000857	R-CARBON;560OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R715	2001-000857	R-CARBON;560OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R719	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R720	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R721	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R803	2003-000994	R-METAL OXIDE(S);33Kohm,5%,2W,AF,TP,3.9x	
R804	2003-000994	R-METAL OXIDE(S);33Kohm,5%,2W,AF,TP,3.9x	
R805	2001-001170	R-CARBON(S);6.8OHM,5%,1/2W,AA,TP,2.4X6.4	
R808	2001-000109	R-CARBON(S);470OHM,5%,1/2W,AA,TP,2.4X6.4	
R809	2001-001150	R-CARBON(S);470KOHM,5%,1/2W,AA,TP,2.4X6.	
R810	2001-001150	R-CARBON(S);470KOHM,5%,1/2W,AA,TP,2.4X6.	
R814	2008-001086	R-FUSIBLE(S);3.3ohm,5%,2W,AG,TP,3.9x12mm	
R815	2008-001086	R-FUSIBLE(S);3.3ohm,5%,2W,AG,TP,3.9x12mm	
R816	2003-002157	R-METAL OXIDE;220OHM,5%,2W,AG,TP,6X16MM	
R817	2004-004089	R-METAL(S);123Kohm,1%,1/2W,AA,TP,2.5x6.5	
R818	2004-001399	R-METAL(S);5.1Kohm,1%,1/2W,AA,TP,2.4x6.4	
R819	2004-001390	R-METAL(S);1Kohm,2%,1/2W,AA,TP,2.4x6.4mm	
R820	2004-001371	R-METAL(S);1.5Kohm,1%,1/2W,AA,TP,2.4x6.4	
R821	2001-001125	R-CARBON(S);300KOHM,5%,1/2W,AA,TP,2.4X6.	
R822	2004-001983	R-METAL(S);2.49Kohm,1%,1/2W,AA,TP,2.4x6.	
R823	2001-000037	R-CARBON(S);330OHM,5%,1/2W,AA,TP,2.4X6.4	
R824	2008-000294	R-FUSIBLE(S);33ohm,5%,2W,AF,TP,3.9x10mm	
R825	2008-000266	R-FUSIBLE(S);1ohm,5%,2W,AF,TP,3.9x10mm	
R826	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R827	2003-000652	R-METAL OXIDE(S);330ohm,5%,2W,AF,TP,4x12	
R828	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R829	2001-000563	R-CARBON;27KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R830	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R831	2001-001192	R-CARBON(S);820OHM,5%,1/2W,AA,TP,2.4X6.4	
R832	2001-001088	R-CARBON(S);1KOHM,5%,1/2W,AA,TP,2.4X6.4M	
R834	2003-001040	R-METAL OXIDE(S);47Kohm,5%,2W,AF,TP,3.9x	
R837	2003-002064	R-METAL OXIDE;7.5ohm,5%,2W,AF,TP,10x3.9m	
R838	2003-002064	R-METAL OXIDE;7.5ohm,5%,2W,AF,TP,10x3.9m	
R839	2003-002064	R-METAL OXIDE;7.5ohm,5%,2W,AF,TP,10x3.9m	
R840	2001-001108	R-CARBON(S);22KOHM,5%,1/2W,AA,TP,2.4X6.4	
R841	2001-000221	R-CARBON;1.2KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R843	2001-000019	R-CARBON(S);10OHM,5%,1/2W,AA,TP,2.4X6.4M	
R850	2001-001170	R-CARBON(S);6.8OHM,5%,1/2W,AA,TP,2.4X6.4	
R901	2001-000472	R-CARBON;2.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R902	2001-000241	R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R903	2001-000472	R-CARBON;2.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R904	2001-000241	R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R905	2001-000005	R-CARBON;390ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R906	2001-000005	R-CARBON;390ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R907	2001-000472	R-CARBON;2.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R908	2001-000472	R-CARBON;2.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R909	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R910	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R911	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R912	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R913	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R914	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R915	2001-000924	R-CARBON;680OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R916	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R917	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R918	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R919	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R920	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R921	2001-000702	R-CARBON;39KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R922	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R923	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R924	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R925	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R926	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R927	2001-000793	R-CARBON;47OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R928	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R933	2001-000628	R-CARBON;300OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R934	2001-000628	R-CARBON;300OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R935	2001-000674	R-CARBON;360OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R937	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R938	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
RM901	AA32-00001A	MODULE REMOCON;-,ORC-195VF,38KHZ,940nm,M	
RX801S	2002-001011	R-COMPOSITION;3.3Mohm,5%,1/2W,AA,TP,3.7x	
RY801S	2002-001012	R-COMPOSITION;8.2Mohm,5%,1/2W,AA,TP,3.7x	
SF101S	2904-000302	FILTER-SAW AV;38.9MHz,SIP5K,ST,15.4dB,B/	
SF102S	2904-001024	FILTER-SAW AV;38.9MHz,SIP5K,TP,18.3dB,PA	
SW801S	3403-000179	SWITCH-PUSH;250V,5A,DPST,-,JPW-2104B	
SW901	3404-000244	SWITCH-TACT;15V,20mA,90-170gf,7.5x7mm,SP	
SW902	3404-000244	SWITCH-TACT;15V,20mA,90-170gf,7.5x7mm,SP	
SW903	3404-000244	SWITCH-TACT;15V,20mA,90-170gf,7.5x7mm,SP	
SW904	3404-000244	SWITCH-TACT;15V,20mA,90-170gf,7.5x7mm,SP	
SW905	3404-000244	SWITCH-TACT;15V,20mA,90-170gf,7.5x7mm,SP	
⚠ T101	AA26-00025A	TRANS-IF;7MG,-,-,-,10pF,-,58.35MHz,7.7x	
⚠ T401	AA26-50001B	TRANS-HORIZ.DRIVE;-,7.1mH,102uH,10-20uH,	
⚠ T444S	AA26-00065A	TRANS FBT;-,FSV-14A004C(S),14-22,125V	
⚠ T801S	AA26-00043A	TRANS SWITCHING;-,-,-,AC90~260V,125/12.5	
⚠ TU01S	AA40-00031A	TUNER-F/S;TAEL-G253D,-,PAL,181CH,38.9MHz	
⚠ V999S	3704-001089	SOCKET-CRT;7P,22.5PI,12PI,SN,-	
VX801S	1405-000187	VARISTOR;750V,1250A,12.5x7mm,TP	
X901	2801-003937	CRYSTAL-UNIT;12MHz,25ppm,28-AAM,30pF,30o	
Z202	2903-001040	FILTER-CERAMIC;TR,5.5/6.0/6.5MHz,-,1dB,-	
	AA39-20010D	LEAD CONNECTOR-ASSY;-,YFH800-01,S,1P,400	
	AA65-30010A	CLAMP-WIRE;NYLON-66,V0,NTR,-,-,-	
	AA65-30111A	CLAMP-WIRE;NYLON,V0,WHT,1T 15MM,ALL MODE	
	6003-000334	SCREW-TAPTITE;RH,+,2S,M3,L6,ZPC(YEL),SWR	

ASSY CABINET FRONT

*	AA91-00068C	ASSY-CABINET,FRONT;-,3338,MLN,V0,WHT
CB+CF	6003-001026	SCREW-TAPTITE;RH,+,B,M4,L15,ZPC(BLK),SWR
CB+RJ	6003-001026	SCREW-TAPTITE;RH,+,B,M4,L15,ZPC(BLK),SWR
CRT+CF	AA60-10050Q	SCREW-ASSY;WC,HH,+,M5,L26.5,SWRCH18A,ZPC
KNOB	6003-001026	SCREW-TAPTITE;RH,+,B,M4,L15,ZPC(BLK),SWR
KNOPOW	AA61-60003J	SPRING-CS;-,SUS304,0.5,OD6,H12,N7,-,-,-
PA+CF	6003-001024	SCREW-TAPTITE;RWH,+,B,M4,L12,ZPC(YEL),SW
	AA64-10052C	KNOB-CONTROL;-,3338,-,ABS,V0,WHT
	AA64-10153E	KNOB-POWER;-,3338,-,ABS,V0,WHT
	AA64-31147L	CABINET-FRONT;-,3338,MLN,ABS,V0,WHT,-,-
	AA61-40010C	BOSS-WING;-,ABS,V0,WHT,-,-
	AA64-40057A	WINDOW-REMOCON;-,3338,-,PC,V0,VIOLET,-
	AA64-40189A	INDICATOR-LED;-,3338,-,ACRYL,-,CLEAR,-
	AA64-70127G	BADGE-BRAND;AL,SAMSUNG,GOLD/WHT,L40,R800
	AA65-30105A	CLAMP-WIRE;NYLON 66,V2,NTR,15MM,ALL MODE
	AA64-01246B	INLAY-COVER;D1,PVC SHEET,T0.4,-,-,-,94VO

Loc. No.	Code No.	Description ; Specification	Remark
	AA64-30381G	CABINET-BACK;-,3338,VE0812,ABS,V0,WHT,-	
	AA65-30008A	CLAMP-CORD;PE,HB,BLK,-,-,-	
	AA65-30106A	CLAMP-D,COIL;NYLON 66,V2,NTR,-,14 INCH,-	

ASSY ACCESSORY

	AA26-90001C	TRANS-MATCHING;-,300ohm/75ohm,PAL,40-890	
	AA42-10001V	ANT-ROD;-,3S,620mm,BRN,UL/CSA	
	AA63-00261C	COVER-JACK;5338,ABS,-,V0,-,WHITE,-	
	AA68-00932A	MANUAL USERS;-,-,B5,-,W/P100(G),-,-,1,-,	

ASSY-CRT

⚠	AA03-10001D	CRT-COLOR;-,A34KQV42X,+380MG,14,90DEG,5	
	AA27-00001A	MAGNET-CONVERGENCE;-,JH225-06A,22.5MM	
⚠	AA27-50004X	DEFLECTION-YOKE;-,DSE-1422FL(G),14/A34K	
	AA63-60028A	SPACER-DY;NEOPRENE,-,BLK,V0 W12,-,-	

ASSY-PCB,A/V FRONT

*	AA95-90027D	ASSY-PCB,A/V FRONT;-,CK5073,SCT13B,CE,9P	
CE01	2401-001840	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
CE03	2401-001989	C-AL;4.7uF,20%,50V,BP,TP,5x11,5	
CE06	2202-000862	C-CERAMIC,MLC-AXIAL;390pF,10%,50V,Y5P,TP	
CE07	2202-000222	C-CERAMIC,MLC-AXIAL;3.3nF,20%,16V,Y5P,TP	
CN702	AA39-20112E	LEAD CONNECTOR-ASSY;-,YBNH025-09,67096-0	
JA702	3722-000506	JACK-RCA;2P,3.6MM,-,AG	
JE601	3722-000143	JACK-PHONE;1P(VER),3.4mm,AG,BLK,NO	
LE01	2701-000158	INDUCTOR-AXIAL;22uH,10%,2.5x3.4mm	
PCB	AA41-10903B	PCB-A/V FRONT;S15A,1L,FR-1,245x245x1.6T,	
QE01	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
RE01	2001-001153	R-CARBON(S);47OHM,5%,1/2W,AA,TP,2.4X6.4M	
RE02	2001-001153	R-CARBON(S);47OHM,5%,1/2W,AA,TP,2.4X6.4M	
RE03	2001-000010	R-CARBON;68KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
RE04	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
RE05	2001-000009	R-CARBON;20KOHM,5%,1/8W,AA,TP,1.8X3.2MM	

ASSY-SPEAKER

*	AA96-00012A	ASSY-SPEAKER;-,-,16OHM 2.5W,3001-000275,	
	3001-000275	SPEAKER;2.5W,16ohm,90dB,105Hz	
	AA39-20501A	LEAD CONNECTOR-ASSY;-,67096-003,REC,3(2)	

ASSY-POWER,CORD

*	AA96-20109B	ASSY-POWER,CORD;-,CP2/NO(4.0),H/C250,KKP	
	AA39-10006X	POWER-CORD;-,KKP419C,KLCE-2F,2.286MT,3P,	
	AA61-20284A	HOLDER;-,P-CORD,PP,VO,BLK,KE-002	

REMOCON

*	AA59-00104E	REMOCON;-,TM59,SIM806E,24,L/GRAY,WHT,P	